

Condition Absolute Stability Control System of Electromagnetoelastic Actuator for Communication Equipment

Sergey Mikhailovich Afonin

National Research University of Electronic Technology (MIET), Moscow, Russia;
eduems@mail.ru

ABSTRACT

We obtained the condition absolute stability on the derivative for the control system of electromagnetoelastic actuator for communication equipment. We applied the frequency methods for Lyapunov stable control system to calculate the condition absolute stability control system of electromagnetoelastic actuator. We used Yakubovich criterion absolute stability system with the condition on the derivative. The aim of this work is to determine the condition of the absolute stability on the derivative for the control system of electromagnetoelastic actuator. We received the stationary set of the control system of the hysteresis deformation of the electromagnetoelastic actuator. The stationary set is the segment of the straight line.

Keywords: Electromagnetoelastic actuator; Piezoactuator; Hysteresis; Control system; Condition absolute stability; Stationary set.

1 Introduction

The application of the electromagnetoelastic actuator based on the electromagneto elasticity as the piezoelectric, piezomagnetic, electrostriction, magnetostriction effects is promising for the control system of electromagnetoelastic actuator for communication equipment. The piezoactuator solves problems of the precise matching in the nanotechnology, the compensation of the temperature and gravitational deformations, the atmospheric turbulence by the wave front correction in adaptive optics. The piezoactuator for the nanotechnology is used in the scanning tunneling microscopes, the scanning force microscopes, the atomic force microscopes [1 – 15].

Piezoactuator is piezomechanical device intended for actuation of mechanisms, systems or management based on the piezoelectric effect, converts the electrical signals into the mechanical movement or the force. The piezoactuators for the drives of nano- and micrometric movements provide the movement range from nanometers to hundred of micrometers, the loading capacity of up to 1000 N, and the transmission band of up to 100 Hz. The piezoactuators are used in the majority of nanomanipulators for adaptive optics and nanomechatronics. The nanorobotic manipulator of nano- and microdisplacements with the electromagnetoelastic actuator is the key component in nanorobotic systems. The main requirement for nanomanipulator with the electromagnetoelastic actuator is to guarantee the positioning accurate to nanometers in communication equipment [14 – 26].

The problems of using condition of absolute stability the control system of the electromagnetoelastic actuator nano- and microdisplacements are discussed [2, 3]. The stationary set of the control system of the electromagnetoelastic actuator is determined.

We obtained condition of the absolute stability on the derivative for the control system with the electromagnetoelastic actuator. The condition of the Yakubovich absolute stability on the derivative for the control system of electromagnetoelastic actuator for communication equipment are determined. The stationary set of the control system of the deformation of the electromagnetoelastic actuator is the segment of the straight line. The condition absolute stability on the derivative for the control systems of the piezoactuator in the case of the longitudinal, transverse and shift piezoeffect for the hysteresis characteristic of the deformation of the piezoactuator are obtained.

2 Stationary set control system of electromagnetoelastic actuator

The analytical expression for the sufficient absolute stability condition of the system with the hysteresis nonlinearity of the electromagnetoelastic actuators is written using the Yakubovich absolute stability criterion with the condition on the derivative [2, 3]. The Yakubovich absolute stability criterion is next development of the Popov absolute stability criterion. For the Lyapunov-stable control system the Yalubovich absolute stability criterion for the systems with the single hysteresis nonlinearity is provided the simplest and pictorial representation of results of the investigation of the stability of the system. We are used the correcting devices of the system ensuring the stability of the strain control systems with the electromagnetoelastic actuators. The aim of this work is to receive the condition of the absolute stability on the derivative for the control system of electromagnetoelastic actuator for communication equipment.

The measurements of the end face movement of the piezoactuator were made using Model 214 electronic measuring system of Caliber plant. The experimental static strain characteristic of the piezoactuator from PZT for longitudinal piezoeffect is shown in Figure 1 with the main hysteresis loop with the symmetrical voltage change and with partial cycle with the asymmetric voltage change on the plates of the piezoactuator.




Figure 1. Hysteresis type characteristic deformation of piezoactuator for longitudinal piezoeffect

In work we use the transfer function of the linear part of the system $W_{ij}(s)$ with operator $s = j\omega$, for s we have j the imaginary unity and ω the frequency, and the hysteresis function of the relative deformation

S_j of the electromagnetoelastic actuator, i and j are axis. We use the transfer function of the linear part of the system $W_{ij}(s)$ and the function of the relative deformation S_j of the electromagnetoelastic actuator for description of the system [3]. The equation of the hysteresis nonlinearity of the electromagnetoelastic actuator has the form

$$S_j = F[\Psi_i|_0^t, t, S_j(0), \text{sign}(d\Psi_i/dt)] \quad (1)$$

where S_j is the relative displacement of the cross section of the actuator along j axis, Ψ_i is the control parameter of the actuator along i axis. The hysteresis function S_j at each time instant t depends on the behavior of the function $\Psi_i = E_i$ or $\Psi_i = H_i$, where E_i and H_i are the electric field strength and the magnetic field strength on the interval $[0, t]$, the value of t , the initial value $S_j(0)$, and the sign of the rate $d\Psi_i/dt$ of the field strength variation. We consider the alternating-sign hysteresis characteristic of the piezoactuator on Figure 1 and Figure 2. We have for the piezoactuator the set $L[E_i(0)]$ in form the vertical segment $[S_j^0, -S_j^0]$ bounded by the points of intersection of the ordinate axis with the hysteresis loop at the maximum admissible field strength in the piezoactuator. For the stable linear part of the control system of the piezoactuator we obtain the straight line D with the equation

$$E_i + k_{ij}S_j = 0 \quad (2)$$

$$k_{ij} = W_{ij}(0)$$

where $k_{ij} = W_{ij}(0)$ is the transmission coefficient of the linear part of the control system, accordingly $W_{ij}(0)$ is the value of the transfer function of the linear part of the control system of the piezoactuator for $\omega = 0$.




Figure 2. Hysteresis type characteristic of piezoactuator

The set of points M for intersection of this straight line D with the hysteresis characteristic represents the segment of the straight line marked in Figure 2 for $E_{i0} = E_i(0)$ and $S_{j0} = S_j(0)$ we have the stationary solution to the control system. The stationary set M of the system is the marked segment of straight line D in Figure 1 with the set of pairs (E_{i0}, S_{j0}) . Each point of intersection of the hysteresis nonlinearity with the partial loops and the straight line D corresponds to one equilibrium position with the coordinates (E_{i0}, S_{j0}) .

The equation of for the main hysteresis loop [3] of the piezoactuator on Figure 2 has the form

$$S_j = d_{ij}E_i - \gamma_{ij}E_{im} \left(1 - \frac{E_i^2}{E_{im}^2}\right)^{n_{ij}} \text{sign}(dE_i/dt), \quad (3)$$

where S_j is the relative displacement of the piezoactuator, E_i is the electric field strength, d_{ij} is the piezomodule, E_{im} is the electric field strength amplitude, γ_{ij} is the hysteresis coefficient, n_{ij} is the power for piezoceramics based on lead zirconate titanate PZT we have $n_{ij} = 1$ and dE_i/dt is the rate of the electric field strength variation. From (2) and (3) we have for the piezoactuator the equation

$$\Delta E_{im} + k_{ij}E_{im}[d_{ij}\Delta - \gamma_{ij}(1 - \Delta^2)] = 0 \quad (4)$$

where Δ is the relative electric field strength at the extreme equilibrium point for the control system of the deformation of the piezoactuator. From (4) after conversion we have the equation

$$\Delta + k_{ij}[d_{ij}\Delta - \gamma_{ij}(1 - \Delta^2)] = 0 \quad (5)$$

We obtain the quadratic equation for determination of the width of the rest domain 2Δ of the piezoactuator for the longitudinal piezoeffect in the form

$$\Delta^2 + \frac{(1+k_{ij}d_{ij})}{k_{ij}\gamma_{ij}}\Delta - 1 = 0 \quad (6)$$

The width of the rest domain 2Δ of the piezoactuator has the form

$$2\Delta = -\frac{(1+k_{ij}d_{ij})}{k_{ij}\gamma_{ij}} + \sqrt{\frac{(1+k_{ij}d_{ij})^2}{k_{ij}^2\gamma_{ij}^2} + 4} \quad (7)$$

The characteristic of the electromagnetoelastic actuators has the alternating-sign hysteresis type for the piezoactuator on Figure 2 or the constant-sign butterfly type for the electrostriction actuator on Figure 3. In the magnetostriction or electrostriction actuator initial operating point is chosen on one wing of the butterfly in the first quadrant. The deformation range has symmetric at both sides of initial point. The initial working point is displaced from zero by the half deformation range.




Figure 3. Butterfly type characteristic of electrostrictive actuator

3 Condition absolute stability of control system of electromagnetoelastic actuator

The analytical expression for the sufficient absolute stability condition of the system with the hysteresis nonlinearity of the electromagnetoelastic actuator is written using the Yakubovich absolute stability criterion with the condition on the derivative. The Yakubovich criterion is the development of the Popov absolute stability criterion. For the Lyapunov-stable control system the Yakubovich absolute stability criterion for the system with the single hysteresis nonlinearity provides the simplest and pictorial representation of results of the investigation of the stability [3]. The correcting devices are chosen for providing the high quality the control system of the deformation of the piezoactuator. The function $S_j(E_i)$ of the hysteresis nonlinearity of the piezoactuator is continuous, then we have quantities

$$v_{1ij}, v_{2ij} \in [0, v_{ij}], v_{ij} = \max(dS_j/dE_i) \quad (8)$$

where the quantities v_{1ij} and v_{2ij} are calculated using the hysteresis static characteristic on Figure 1 measured at the maximum admissible electric field strength in the piezoactuator. The quantities $v_{1ij} = 0$ and $v_{2ij} = v_{ij}$ are the minimum and the maximum values of the tangent of the inclination angle of the tangent line to the hysteresis nonlinearity of the piezoactuator. We obtain the following equation

$$v_{33}:v_{31}:v_{15} = d_{33}:d_{31}:d_{15} \quad (9)$$

where the ratios of the tangents of the inclination angle of the tangent line to the hysteresis nonlinearity of the piezoactuator for longitudinal, transverse and shift piezoeffects are proportional to the ratios of the piezomodules. The sufficient Yakubovich absolute stability condition of the control system of the deformation [4–7] of the actuator have the form

$$\operatorname{Re} v_{ij}W_{ij}(j\omega) \geq -1 \quad (10)$$

where in brackets j is the imaginary unity and ω is the frequency. The amplitude-phase characteristic of the open-loop system $v_{ij}W_{ij}(j\omega)$ should be situated on Figure 4 to right of the straight line

$$\operatorname{Re} v_{ij}W_{ij}(j\omega) = -1 \quad (11)$$

for all $\omega \geq 0$ and the corrected amplitude frequency characteristic is to right of this straight line.




Figure 4. Condition absolute stability control system of electromagnetoelastic actuator for communication equipment is met for shaded corrected amplitude frequency characteristic

The Yakubovich absolute stability criterion (11) on Figure 4 is simple and convenient for synthesis of correcting devices for the control system.

We have the absolute stability criterion for the system on Figure 5 in the plane of the logarithmic amplitude frequency characteristic and the phase frequency characteristic

$$L(\omega) = Q[\varphi(\omega)], \quad L(\omega) = 20\lg|v_{ij}W_{ij}(j\omega)| \quad (12)$$

where the corrected logarithmic amplitude frequency characteristic is below the boundary curve in the following form




Figure 5. Condition absolute stability control system of electromagnetoelastic actuator for communication equipment is met for shaded corrected logarithmic amplitude frequency characteristic

For the piezoactuator from PZT the value of the maximum tangent of the inclination angle of the tangent line to the nonlinearity is about 1 nm/V for longitudinal piezoeffect and about 0.6 nm/V for transverse piezoeffect. The characteristics of the correcting device for the control system are determined from the condition of the absolute stability of control system.

4 Conclusion

We have the stationary set of the control system of the deformation of the electromagnetoelastic actuator in the form of the segment of the straight line. We used Yakubovich criterion absolute stability system and the frequency methods for Lyapunov stable control system to calculate the condition absolute stability control system. We received condition of the absolute stability on the derivative for the control system with the electromagnetoelastic actuator for communication equipment.

REFERENCES

- [1]. Schultz, J., Ueda, J., Asada, H., *Cellular actuators*. Oxford: Butterworth-Heinemann Publisher, 2017. 382 p.
- [2]. Yakubovich, V.A., Popov's method and its subsequent development. *European Journal of Control*, 2002. 8(3): p.200-208, doi:10.3166/ejc.8.200-208.

- [3]. Afonin, S.M., *Absolute stability of a piezotransducer deformation control system*. Journal of Computer and Systems Sciences International. New York: Pleiades publishing, Inc., Springer, 2005. 44(2): p. 266 – 272.
- [4]. Zhou, S., Yao, Z., *Design and optimization of a modal-independent linear ultrasonic motor*. IEEE Transaction on Ultrasonics, Ferroelectrics, and Frequency Control, 2014. 61(3): p. 535-546, doi:10.1109/TUFFC.2014.2937.
- [5]. Przybylski, J., *Static and dynamic analysis of a flextensional transducer with an axial piezoelectric actuation*. Engineering Structures, 2015. 84: p. 140-151, doi:10.1016/j.engstruct.2014.11.025.
- [6]. Ueda, J., Secord, T., Asada, H.H., *Large effective-strain piezoelectric actuators using nested cellular architecture with exponential strain amplification mechanisms*. IEEE/ASME Transactions on Mechatronics, 2010. 15(5): p. 770-782, doi:10.1109/TMECH.2009.2034973.
- [7]. Karpelson, M., Wei, G.-Y., Wood, R.J., *Driving high voltage piezoelectric actuators in microrobotic applications*. Sensors and Actuators A: Physical, 2012. 176: p. 78-89, doi:10.1016/j.sna.2011.11.035.
- [8]. Afonin, S.M., *Block diagrams of a multilayer piezoelectric motor for nano- and microdisplacements based on the transverse piezoeffect*. Journal of Computer and Systems Sciences International, 2015. 54(3): p. 424-439, doi:10.1134/S1064230715020021.
- [9]. Afonin, S.M., *Structural parametric model of a piezoelectric nanodisplacement transducer*. Doklady Physics, 2008. 53(3): p. 137-143, doi:10.1134/S1028335808030063.
- [10]. Afonin, S.M., *Solution of the wave equation for the control of an electromagnetoelastic transducer*. Doklady Mathematics, 2006. 73(2): p. 307-313, doi:10.1134/S1064562406020402.
- [11]. Cady W.G., *Piezoelectricity: An introduction to the theory and applications of electromechanical phenomena in crystals*. New York, London: McGraw-Hill Book Company, 1946. 806 p.
- [12]. *Physical acoustics: Principles and methods. Vol.1. Part A. Methods and devices*. Mason, W., Editor, New York: Academic Press, 1964. 515 p.
- [13]. Zwillinger, D., *Handbook of differential equations*. Boston: Academic Press, 1989. 673 p.
- [14]. Afonin, S.M., *Structural-parametric model and transfer functions of electroelastic actuator for nano- and microdisplacement*. Chapter 9 in Piezoelectrics and nanomaterials: Fundamentals, developments and applications. Parinov, I.A., Editor, New York: Nova Science, 2015. p. 225-242.
- [15]. Afonin, S.M., *A structural-parametric model of electroelastic actuator for nano- and microdisplacement of mechatronic system*. Chapter 8 in Advances in nanotechnology. Volume 19. Bartul, Z., Trenor, J., Editors, New York: Nova Science, 2017. p. 259-284.
- [16]. Afonin, S.M., *A block diagram of electromagnetoelastic actuator nanodisplacement for communications systems*. Transactions on Networks and Communications, 2018, 6(3): p. 1-9, doi:10.14738/tnc.63.4641.
- [17]. Afonin, S.M., *Structural-parametric model electromagnetoelastic actuator nanodisplacement for mechatronics*. International Journal of Physics, 2017, 5(1): p. 9-15, doi: 10.12691/ijp-5-1-2.

- [18]. Afonin, S.M., *Decision matrix equation and block diagram of multilayer electromagnetoelastic actuator micro and nanodisplacement for communications systems*, Transactions on Networks and Communications, 2019. 7(3): p. 11-21, doi:10.14738/tnc.73.6564.
- [19]. Afonin, S.M., *Nano- and micro-scale piezomotors*. Russian Engineering Research, 2012. 32(7-8): p.519-522, doi:10.3103/S1068798X12060032.
- [20]. Afonin, S.M., *Elastic compliances and mechanical and adjusting characteristics of composite piezoelectric transducers*. Mechanics of Solids, 2007. 42(1): p. 43-49, doi:10.3103/S0025654407010062.
- [21]. Afonin, S.M., *Structural-parametric model multilayer electromagnetoelastic actuator for nanomechanics*. International Journal of Physics, 2019. 7(2): p.50-57. doi: 10.12691/ijp-7-2-3.
- [22]. Afonin, S.M., *Structural-parametric model of electromagnetoelastic actuator for nanomechanics*. Actuators, 2018. 7(1): p.1-9, doi:10.3390/act7010006.
- [23]. Afonin, S.M., *Structural-parametric model and diagram of a multilayer electromagnetoelastic actuator for nanomechanics*. Actuators, 2019. 8(3): p.1-14, doi:10.3390/act8030052.
- [24]. Afonin, S.M., *Structural-parametric model actuator of adaptive optics for composite telescope and astrophysics equipment*. Physics and Astronomy International Journal, 2020. 4(1): p.18–21, doi:10.15406/paij.2020.04.00198.
- [25]. Uchino K., *Piezoelectric actuator and ultrasonic motors*. Boston, MA: Kluwer Academic Publishers, 1997. 347 p
- [26]. *Springer Handbook of Nanotechnology*. Bhushan, B., Editor, Berlin, New York: Springer, 2004. 1222 p.